

ACT-300/311/312 WIRELESS FREQUENCY MATRIX (6B Code)

CH	Group										
	1	2	3	4	5	6	7	8	9	10	11
1	645.275	645.525	645.775	646.025	644.100	645.675	644.950	644.425	644.200	645.525	***.***
2	646.075	646.325	646.575	646.825	645.700	647.175	645.800	644.925	644.700	646.050	***.***
3	652.400	652.650	652.900	653.150	651.100	651.175	646.300	645.675	645.450	647.025	***.***
4	657.225	657.475	657.725	657.975	653.200	654.675	647.050	646.175	645.950	647.450	***.***
5	660.800	661.050	661.300	661.550	659.600	657.675	648.050	647.675	647.450	650.150	***.***
6	663.125	663.375	663.625	663.875	663.300	662.675	648.650	648.275	648.050	650.675	***.***
7	664.900	665.150	665.400	665.650	664.400	664.675	650.650	650.000	649.775	651.725	***.***
8	666.125	666.375	666.625	666.875	667.600	667.175	655.750	651.350	651.125	652.175	***.***
9							658.250	659.625	659.400	659.675	
10							658.950	660.450	660.225	660.100	
11							661.725	661.025	660.800	661.275	
12							662.400	661.850	661.625	661.825	
13							664.950	663.600	663.375	664.400	
14							665.450	664.525	664.300	664.925	
15							666.300	665.100	664.875	666.050	
16							666.800	665.925	665.700	666.475	

ACT300-656A.1

(MHz)

MA-101a/MA-101A/MA-202/MRM-70-R FREQUENCY MATRIX (6B code)

0 CH	645.525	8 CH	659.675
1 CH	646.050	9 CH	660.100
2 CH	647.025	A CH	661.275
3 CH	647.450	B CH	661.825
4 CH	650.150	C CH	664.400
5 CH	650.675	D CH	664.925
6 CH	651.725	E CH	666.050
7 CH	652.175	F CH	666.475